

迷你攜帶式 Mifare/Felica UID Reader/

資料採集終端機

介紹:

MFR120 是一個攜帶型資料採集終端機，它擁有最新 RFID 技術。**MFR120** 可讀 **Mifare/Felica** UID 外，還具備了內建 LCD 及時間計數器(real time clock)的特性。

MFR120 輕便、體積小且省電，讓使用者可以隨時隨地不受場地影響的收集資料。

如何使用 **MFR120** ?

“**ONE-TOUCH**” 設計，簡單讀取 **Mifare/Felica** 卡片並顯示在螢幕上，不僅如此也同時紀錄在記憶體中，可隨時讓電腦進行下載。

特點:

- 支援 512K bytes 記憶體
- 內建 Built-in Real Time Clock (RTC)作為時間計數
- 使用標準 AAA 電池,容易取得方便更換
- 可讀 13.56MHz Mifare 及 Felica cards
- 支援 LCD 顯示器 (101 x 67 dots)
- 自動省電裝置
- 低電量提醒裝置
- 記憶量不足提醒裝置
- 精巧設計，重量僅有 50 公克重(含電池)

應用:

- 員工出勤資料採集
- 參觀人員/Buyer 的管理
- 會議報到管理
- 巡邏系統
- 學生出缺管理

規格:

Model	MFR120	MFR120U
Specification		
可讀取卡片種類	13.56 MHz Mifare standard:1K, 4K, Ultralight, DESfire	
	13.56MHz Felica standard	
LCD 顯示	紅燈/綠燈 指示燈 電力顯示及時間顯示	
顯示器	FSTN 101 x 67 dots	
記憶容量/儲存筆數	512K bytes Up to 8192 records (32 Bytes/Record)	
電池	Single-cell Size AAA 1.5V DC Battery	
CABLE 電源供應	DC5V, 200mA RS232 or USB interface	
界面	RS232, 19200, N, 8, 1, half-duplex	USB
認證	FCC/CE	
尺寸	L58 X W20 X H47 mm	
工作環境	Operation temp: 0 ~ 55 degree C Humidity: 10 ~ 90% relative	

Ordering information:

- **MFR120** – RS232 界面
- **MFR120U** – USB 界面

※Specification is subject to change without notice.



Exhibitions Data Collection



Construction Site Time Attendance

We welcome OEM inquiries

- Custom design manufacturing is available
- Custom device programming is available
- Call factory for other configuration



8F.,NO.31, LANE 169, KANG-NING STREET,HSI-CHIH,TAIPEI,TAIWAN

TEL: 886-2-26954214

FAX: 886-2-26954213

e-mail: promag@gigatms.com.tw

http://www.gigatms.com.tw



MFR120

Mini Portable Mifare/Felica UID Reader/ Data Collection Terminal